



DE985TN

HF Drivers - 2.0 Inches

220 W continuous program power capacity
 2" horn throat diameter
 75 mm (3 in) CCAW voice coil
 Titanium diaphragm
 500 - 18000 Hz response
 108.5 dB sensitivity
 Neodymium magnet assembly with shorting copper cap

Specifications¹

Throat diameter	50 mm (2.0 in)
Nominal impedance	8 Ω
Minimum impedance	8.1 Ω
Nominal power handling ²	110 W
Continuous power handling ³	220 W
Sensitivity (1W/1m) ⁴	108.5 dB
Frequency range	1 - 18 kHz
Recommended crossover ⁵	1.2 kHz
Voice coil diameter	75 mm (3.0 in)
Winding material	Aluminium
Inductance	0.1 mH
Diaphragm material	Titanium
Flux density	2.05 T
Magnet material	Neodymium Ring

Mounting And Shipping Info

Depth	87 mm (3.44 in)
Net weight	2.5 kg (5.51 lb)
Shipping units	4
Shipping weight	10.6 kg (23.37 lb)
Shipping box	300x160x180 mm (11.8x6.3x7.1 in)

Replacement Diaphragm

MMD3DTN8M

Mounting And Shipping Info

Four M6 holes 90° on 102 mm (4 in) diameter	
Overall diameter	131 mm (5.2 in)

1. Driver mounted on B&C ME60 horn

2. 2 hour test made with continuous pink noise signal (6 dB crest factor) within the range from the recommended crossover frequency to 20 kHz. Power calculated on rated minimum impedance.

3. Power on Continuous Program is defined as 3 dB greater than the Nominal rating.

4. Applied RMS Voltage is set to 2.83 V for 8 ohms Nominal Impedance.

5. 12 dB/oct. or higher slope high-pass filter.